

Low-current voltage regulator diodes Rev. 3 — 18 January 2023

Product data sheet

1. General description

Low-current voltage regulator diodes in a small SOD323 (SC-76) Surface-Mounted Device (SMD) plastic package.

2. Features and benefits

- Total power dissipation: ≤ 300 mW
- Tolerance series: approximately ± 5 % •
- Working voltage range: nominal 1.8 V to 10 V •
- Specified at a low test current (50 µA), ideal for low bias and portable battery-powered applications

3. Applications

Low-current general regulation functions

4. Quick reference data

Table 1. Quick reference data

Symbol	Parameter	Conditions	Min	Тур	Max	Unit
V _F	forward voltage	I _F = 10 mA [1]	-	-	0.9	V
P _{tot}	total power dissipation	T _{amb} ≤ 25 °C [2]	-	-	300	mW

Pulse test: $t_p \le 300 \ \mu s$; $\delta \le 0.02$ [1]

[2] Device mounted on an FR4 Printed-Circuit Board (PCB), single-sided copper, tin-plated and standard footprint.

5. Pinning information

Table 2. Pinning

Pin	Symbol	Description	Simplified outline	Graphic symbol
1	к	cathode [1]		К KA
2	A	anode		006aaa152

[1] The marking bar indicates the cothode.



6. Ordering information

Table 3. Ordering information					
Type number	Package	ickage			
	Name	Description	Version		
BZX38450 series	SC-76	plastic surface-mounted package; 2 leads	SOD323		

7. Marking

Table 4. Marking Codes	<u> </u>		
Type number	Marking Code	Type number	Marking Code
BZX38450-C1V8	6R	BZX38450-C4V7	7в
BZX38450-C2V0	6S	BZX38450-C5V1	7C
BZX38450-C2V2	6T	BZX38450-C5V6	7D
BZX38450-C2V4	6U	BZX38450-C6V2	7E
BZX38450-C2V7	6V	BZX38450-C6V8	7F
BZX38450-C3V0	6W	BZX38450-C7V5	7G
BZX38450-C3V3	6X	BZX38450-C8V2	7н
BZX38450-C3V6	6Y	BZX38450-C9V1	7J
BZX38450-C3V9	6Z	BZX38450-C10	7К
BZX38450-C4V3	7A	-	-

8. Limiting values

Table 5. Limiting values

In accordance with the Absolute Maximum Rating System (IEC 60134).

Symbol	Parameter	Conditions		Min	Max	Unit
I _F	forward current			-	250	mA
P _{ZSM}	non-repetitive peak reverse power dissipation	t _p = 100 μs; square wave; T _j = 25 °C; prior to surge		-	40	W
P _{tot}	total power dissipation	T _{amb} ≤ 25 °C	[1]	-	300	mW
Tj	junction temperature			-	150	°C
T _{amb}	ambient temperature			-55	+150	°C
T _{stg}	storage temperature			-65	+150	°C

[1] Device mounted on an FR4 Printed-Circuit Board (PCB), single sided copper, tin-plated and standard footprint.

9. Thermal characteristics

Table 6. Thermal characteristics

Symbol	Parameter	Conditions	Min	Тур	Max	Unit
R _{th(j-a)}	thermal resistance from junction to ambient	in free air [1]	-	-	415	K/W
R _{th(j-sp)}	thermal resistance from junction to solder point	[2]	-	-	110	K/W

[1] Device mounted on an FR4 Printed-Circuit Board (PCB), single sided copper, tin-plated and standard footprint.

[2] Soldering point of cathode tab

10. Characteristics

Table 7. Electrical characteristics

 T_i = 25 °C unless otherwise specified.

Symbol	Parameter	Conditions		Мах	Unit
V _F	forward voltage	I _F = 10 mA	[1]	0.9	V

[1] Pulse test: $t_p \le 300 \ \mu s; \delta \le 0.02$


Table 8. Electrical characteristics per type: BZX38450-C1V8 to BZX38450-C10

T_j = 25 °C unless otherwise specified.


BZX38450-C		Working voltage V _Z (V)		Differential resistance r _{diff} (Ω)		Reverse current I _R (μΑ)		nperature efficient (mV/K)	Diode capacit. C _d (pF)[1]	
	I _Z = 50 μA		I _Z = 1 mA I _Z = 5 mA				I _Z = 5 mA			
	Min	Max	Max	Max	Max	V _R (V)	Min	Max	Мах	
1V8	1.71	1.89	600	100	7.5	1.0	-3.5	0	220	
2V0	1.88	2.12	600	100	7	1.0	-3.5	0	220	
2V2	2.09	2.31	600	100	4	1.0	-3.5	0	210	
2V4	2.28	2.52	600	100	2	1.0	-3.5	0	200	
2V7	2.565	2.835	600	100	1	1.0	-3.5	0	190	
3V0	2.85	3.15	600	100	0.8	1.0	-3.5	0.2	170	
3V3	3.13	3.47	600	100	7.5	1.5	-3.5	1.2	160	
3V6	3.42	3.78	600	95	7.5	2.0	-3.5	1.2	160	
3V9	3.70	4.10	600	95	5.0	2.0	-2.7	2.5	150	
4V3	4.09	4.52	600	95	4.0	2.0	-2.7	2.5	150	
4V7	4.47	4.94	600	80	5.0	3.0	-2.7	2.5	140	
5V1	4.85	5.36	500	60	5.0	3.0	-2.0	3.7	130	
5V6	5.32	5.88	400	40	2.0	4.0	-2.0	3.7	120	
6V2	5.89	6.51	160	10	1.0	5.0	0.4	4.5	110	
6V8	6.46	7.14	80	15	0.1	5.1	1.2	4.5	100	
7V5	7.13	7.88	80	15	0.1	5.7	2.5	5.3	150	
8V2	7.79	8.61	80	15	0.1	6.2	3.2	6.2	150	
9V1	8.65	9.56	100	15	0.1	6.9	3.8	7.0	150	
10	9.50	10.50	150	20	0.1	7.6	4.5	8.0	90	

[1] f = 1 MHz; V_R = 0 V


Low-current voltage regulator diodes



Low-current voltage regulator diodes



11. Package outline



BZX38450_SER

Low-current voltage regulator diodes

12. Soldering





Fig. 8. Reflow soldering footprint SOD323 (SC-76)



Product data sheet

© Nexperia B.V. 2023. All rights reserved

7/10

13. Revision history

Table 9. Revision history					
Document ID	Release date	Data sheet status	Change notice	Supersedes	
BZX38450_SER v.3	20230118	Product data sheet	-	BZX38450_SER v.2	
Modifications:	Products remov	Products removed: 11 V and higher			
BZX38450_SER v.2	20210825	Product data sheet	-	BZX38450_SER v.1	
BZX38450_SER v.1	20210427	Objective data sheet	-	-	

BZX38450_SER

Low-current voltage regulator diodes

14. Legal information

Data sheet status

Document status [1][2]	Product status [3]	Definition
Objective [short] data sheet	Development	This document contains data from the objective specification for product development.
Preliminary [short] data sheet	Qualification	This document contains data from the preliminary specification.
Product [short] data sheet	Production	This document contains the product specification.

 Please consult the most recently issued document before initiating or completing a design.

- [2] The term 'short data sheet' is explained in section "Definitions".
- [3] The product status of device(s) described in this document may have changed since this document was published and may differ in case of multiple devices. The latest product status information is available on the internet at <u>https://www.nexperia.com</u>.

Definitions

Draft — The document is a draft version only. The content is still under internal review and subject to formal approval, which may result in modifications or additions. Nexperia does not give any representations or warranties as to the accuracy or completeness of information included herein and shall have no liability for the consequences of use of such information.

Short data sheet — A short data sheet is an extract from a full data sheet with the same product type number(s) and title. A short data sheet is intended for quick reference only and should not be relied upon to contain detailed and full information. For detailed and full information see the relevant full data sheet, which is available on request via the local Nexperia sales office. In case of any inconsistency or conflict with the short data sheet, the full data sheet shall prevail.

Product specification — The information and data provided in a Product data sheet shall define the specification of the product as agreed between Nexperia and its customer, unless Nexperia and customer have explicitly agreed otherwise in writing. In no event however, shall an agreement be valid in which the Nexperia product is deemed to offer functions and qualities beyond those described in the Product data sheet.

Disclaimers

Limited warranty and liability — Information in this document is believed to be accurate and reliable. However, Nexperia does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information. Nexperia takes no responsibility for the content in this document if provided by an information source outside of Nexperia.

In no event shall Nexperia be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, Nexperia's aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the Terms and conditions of commercial sale of Nexperia.

Right to make changes — Nexperia reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

Suitability for use — Nexperia products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of an Nexperia product can reasonably be expected to result in personal

injury, death or severe property or environmental damage. Nexperia and its suppliers accept no liability for inclusion and/or use of Nexperia products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Quick reference data — The Quick reference data is an extract of the product data given in the Limiting values and Characteristics sections of this document, and as such is not complete, exhaustive or legally binding.

Applications — Applications that are described herein for any of these products are for illustrative purposes only. Nexperia makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using Nexperia products, and Nexperia accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the Nexperia product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

Nexperia does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using Nexperia products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). Nexperia does not accept any liability in this respect.

Limiting values — Stress above one or more limiting values (as defined in the Absolute Maximum Ratings System of IEC 60134) will cause permanent damage to the device. Limiting values are stress ratings only and (proper) operation of the device at these or any other conditions above those given in the Recommended operating conditions section (if present) or the Characteristics sections of this document is not warranted. Constant or repeated exposure to limiting values will permanently and irreversibly affect the quality and reliability of the device.

Terms and conditions of commercial sale — Nexperia products are sold subject to the general terms and conditions of commercial sale, as published at <u>http://www.nexperia.com/profile/terms</u>, unless otherwise agreed in a valid written individual agreement. In case an individual agreement is concluded only the terms and conditions of the respective agreement shall apply. Nexperia hereby expressly objects to applying the customer's general terms and conditions with regard to the purchase of Nexperia products by customer.

No offer to sell or license — Nothing in this document may be interpreted or construed as an offer to sell products that is open for acceptance or the grant, conveyance or implication of any license under any copyrights, patents or other industrial or intellectual property rights.

Export control — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from competent authorities.

Non-automotive qualified products — Unless this data sheet expressly states that this specific Nexperia product is automotive qualified, the product is not suitable for automotive use. It is neither qualified nor tested in accordance with automotive testing or application requirements. Nexperia accepts no liability for inclusion and/or use of non-automotive qualified products in automotive equipment or applications.

In the event that customer uses the product for design-in and use in automotive applications to automotive specifications and standards, customer (a) shall use the product without Nexperia's warranty of the product for such automotive applications, use and specifications, and (b) whenever customer uses the product for automotive applications beyond Nexperia's specifications such use shall be solely at customer's own risk, and (c) customer fully indemnifies Nexperia for any liability, damages or failed product claims resulting from customer design and use of the product for automotive applications beyond Nexperia's standard warranty and Nexperia's product specifications.

Translations — A non-English (translated) version of a document is for reference only. The English version shall prevail in case of any discrepancy between the translated and English versions.

Trademarks

Notice: All referenced brands, product names, service names and trademarks are the property of their respective owners.

Contents

1.	General description	1
2.	Features and benefits	. 1
3.	Applications	. 1
4.	Quick reference data	1
5.	Pinning information	1
6.	Ordering information	2
7.	Marking	2
8.	Limiting values	. 3
9.	Thermal characteristics	. 3
10.	Characteristics	4
11.	Package outline	. 6
12.	Soldering	. 7
13.	Revision history	8
14.	Legal information	9

© Nexperia B.V. 2023. All rights reserved

For more information, please visit: http://www.nexperia.com For sales office addresses, please send an email to: salesaddresses@nexperia.com Date of release: 18 January 2023

BZX38450_SER